

((••)) Elatec RFID Systems		TWN4 MULTITECH (125kHz + 134.2kHz + 13.56MHz + NFC + Bluetooth Low Energy)					
with Antenna →	MultiTech HF Mini Reader	MultiTech 2 BLE	MultiTech 2 BLE P	MultiTech 2 BLE PI	MultiTech LEGIC	MultiTech LEGIC P	
		MultiTech Core	MultiTech Core P	MultiTech Core PI	MultiTech Core LEGIC	MultiTech Core LEGIC P	
without Antenna →		MultiTech Nano	MultiTech Nano P	MultiTech Nano PI	MultiTech Nano LEGIC	MultiTech Nano LEGIC P	
13.56MHZ	ISO14443A	LEGIC Advant	✓ 1)	✓ 1)	✓ 1)	✓	✓
		MIFARE Classic	✓	✓	✓	✓	✓
		MIFARE Classic EV1	✓ 5)	✓ 5)	✓ 5)	✓ 5)	✓ 5)
		MIFARE Mini	✓	✓	✓	✓ 2)	✓ 2)
		MIFARE DESFire EV1	✓	✓	✓	✓	✓
		MIFARE Plus S, X	✓	✓	✓	✓	✓
		MIFARE Pro X	✓ 6)	✓ 6)	✓ 6)	✓ 6)	✓ 6)
		MIFARE Smart MX	✓ 6)	✓ 6)	✓ 6)	✓ 6)	✓ 6)
		MIFARE Ultralight	✓	✓	✓	✓	✓
		MIFARE Ultralight C	✓	✓	✓	✓	✓
		MIFARE Ultralight EV1	✓	✓	✓	✓	✓
		NTAG2xx	✓	✓	✓	✓	✓
		PayPass	✓ 6)	✓ 6)	✓ 6)	✓ 6)	✓ 6)
		SLE44R35	✓	✓	✓	✓ 2)	✓ 2)
	SLE66Rxx (my-d move)	✓	✓	✓	✓	✓	
	ISO14443B	Calypso	✓ 6)	✓ 6)	✓ 6)	✓ 6)	✓ 6)
		CEPAS	✓ 6)	✓ 6)	✓ 6)	✓ 6)	✓ 6)
		Moneo	✓ 6)	✓ 6)	✓ 6)	✓ 6)	✓ 6)
		Pico Pass	✓ 1)	✓ 1)	✓ 1)	✓ 1)	✓ 1)
		SRI4K, SRIX4K	✓	✓	✓	✓	✓
		SRI512, SRT512	✓	✓	✓	✓	✓
	ISO18092/ECMA-340	NFC Forum Tag 1-5	✓ 3)	✓ 3)	✓ 3)	✓ 3)	✓ 3)
		NFC Peer-to-Peer	✓	✓	✓	✓	✓
	ISO15693	Sony FeliCa	✓ 7)	✓ 7)	✓ 7)	✓ 7)	✓ 7)
		EM4x33	✓ 6)	✓ 6)	✓ 6)	✓ 6)	✓ 6)
		EM4x35	✓ 6)	✓ 6)	✓ 6)	✓ 6)	✓ 6)
		HID iCLASS	✓ 1)	✓ 1)	✓ 1)	✓ 10)	✓ 1)
		HID iCLASS SE/SR	✓ 1)	✓ 1)	✓ 1)	✓ 10)	✓ 1)
		ICODE SLI	✓	✓	✓	✓	✓
		LEGIC Advant	✓ 1)	✓ 1)	✓ 1)	✓ 1)	✓
M24LR16/64		✓	✓	✓	✓	✓	
MB89R118/119		✓	✓	✓	✓	✓	
SRF55Vxx (my-d vicinity)		✓ 6)	✓ 6)	✓ 6)	✓ 6)	✓ 6)	
Tag-it	✓	✓	✓	✓	✓		
125kHz / 134.2kHz	LEGIC Prime				✓	✓	
	AWID		✓	✓	✓	✓	
	Cardax		✓	✓	✓	✓ 9)	
	CASI-RUSCO		✓	✓	✓	✓	
	Cotag			✓	✓	✓	
	EM4100, 4102, 4200		✓	✓	✓	✓	
	EM4050, 4150, 4450, 4550		✓	✓	✓	✓	
	EM4305		✓ 4)	✓ 4)	✓ 4)	✓ 4)	
	FDX-B, EM4105		✓	✓	✓	✓	
	G-Prox			✓ 9)	✓ 9)	✓ 9)	
	HID DuoProx II (1336)			✓	✓	✓	
	HID ISO Prox II (1386)			✓	✓	✓	
	HID Micro Prox (1391)			✓	✓	✓	
	HID ProxKey III (1346)			✓	✓	✓	
	HID Prox			✓	✓	✓	
	HID Prox II (1326)			✓	✓	✓	
	HITAG 1, 2, S		✓ 8)	✓ 8)	✓ 8)	✓ 8)	
	Indala			✓	✓	✓	
	ioProx			✓	✓	✓	
	Keri		✓	✓	✓	✓	
	Miro		✓	✓	✓	✓	
	Nedap		✓	✓	✓	✓ 9)	
	Nexwatch			✓	✓	✓	
	Pyramid		✓	✓	✓	✓	
	Q5		✓	✓	✓	✓	
	T5557, T5567, T5577		✓	✓	✓	✓	
	TIRIS/HDX		✓	✓	✓	✓	
	TITAN (EM4050)		✓	✓	✓	✓	
	UNIQUE		✓	✓	✓	✓	
	ZODIAC		✓	✓	✓	✓	

1) UID only 2) UID Only, read/write on request 3) NFC Forum Tag 1 on request only 4) on request 5) r/w, enhanced security features planned 6) r/w in direct chip command mode 7) UID + r/w public area

8) Without crypto 9) Hash value only 10) UID + PAC (CSN & Facility Code), r/w on request

Elatec reserves the right to change any information or data in this document without prior notice. The distribution and the update of this document is not controlled. Elatec declines all responsibility for the use of its products with any other specifications but the ones mentioned above. Any additional requirement for a specific customer application has to be validated by the customer himself at his own responsibility. Where application information is given, it is only advisory and does not form part of the specification.